

OBO-3055 Switch Amplifier and Microphone Power Module

Uses :

Design to use with EAM-1014 & anechoic box. For more analog signal in/out channel and control anechoic box.



Specifications:

- **10 Mic input Channels**
With ICP type mic power supply (can turn off the power by switch)
- **5 Amplifier Output Channels**
For sound source or artificial mouth, 0~20 dB gain
- **3 Output Channels**
Without any AMP.
- **AMP Output:**
Gain: 0~20dB
Frequency Response Flatness: 20Hz~20kHz ± 0.2 dB
Cross Talk: -80dB
Internal Noise: -105dBV
- **Reference Mic Input :**
Microphone Power Supply Voltage: 1.5V~32V
Frequency Response Flatness: 20Hz~20kHz ± 0.02 dB